**Specification** 

# **Smart Valve Positioner 300 Series**

Model AVP300/AVP301/AVP302

## **OVERVIEW**

azbi

Smart Valve Positioner 300 Series Models AVP300/AVP301/ AVP302 are current-pneumatic smart valve positioners. The 300 Series receives a DC current signal from control devices and controls pneumatic valves. In addition to this basic function, the 300 Series has communication capabilities, automatic configuration program, and self diagnostics functions that will greatly increase productivity and the efficiency of plant operation.

The model AVP301 has a valve travel transmitter function which transmits a 4–20 mA DC signal. The model AVP302 has a HART communication protocol.

# **FEATURES**

### 1. Easy to use

#### Auto setup

The auto-setup function is a fully-automatic configuration program which specifies the actuator and adjusts the zero and span of the valve. The program can be turned on simply from an external switch so that adjustments to the valve can be performed quickly and safely in hazardous areas.

#### 2. Single model for multiple specifications

The 300 Series' settings can be changed without replacing any parts. A single model can be modified to suit any application.

#### Input range:

Configurable to any required range for split range

Flow characteristic:

Linear, EQ%, Quick opening or custom user characteristics

Actuator type:

Single or double acting actuator (optional reversing relay required)

## 3. Valve diagnostic (Model AVP302 only)

Following parameters can be monitored by HART communicator or Control Valve Maintenance Support System "Valstaff".

- Stick Slip
- Total Stroke
- Travel Histogram
- Cycle Count
- Shut-Off Count
- Max. Travel Speed



#### 4. Positive seating

The positive seating function completely shuts off the valve if the input signal becomes lower than previously set. This in turn enhances the full shut-off capabilities of the valves.

#### 5. Easy maintenance

The electrical circuit section and air circuit section are completely separate, making the maintenance of the air circuit section at the work site easy. An Auto/Manual switch is standard equipment, so it is also easy to check the operation of the valve. (However, it is not available for the double-acting actuator.)

## 6. Travel transmission

The model AVP301 transmits a 4–20 mA signal proportional to the valve travel. The valve travel can be monitored from the control room.

# 7. Can be mounted on either a single or double-acting actuator.

On a double-acting actuator, a reversing relay is added at the output air pressure connector.

#### No. SS2-AVP300-0100

The wiring method differs depending on whether this device is used as a normal current-pneumatic positioner or as a positioner with a travel transmission function. When using this device as a normal current-pneumatic positioner, it is necessary only to connect the positioner to the host controller with an input signal cable (4–20 mA DC) as with previous models. Figures 1 and 2 show the wiring diagrams.









\*1. For load resistance, refer to Figure 3.



Figure 3. Supply voltage for travel transmission vs. load resistance characteristic

Note) Supply voltage shall be limited to 45 V DC

\*2. Load resistance = Resistance for Monitoring system + 250  $\Omega^{*1}$  + Resistance of supply voltage<sup>\*1</sup>

Table 1. Actuator stroke and accuracy						
Actuator	Stroke (mm)	Accuracy [% F.S.]				
PSA1, 2	14.3, 20, 25	1.0				
PSA3, 4	20, 38	1.0				
TTA 1	6, 8, 10	3.0				
HA1	14.3, 25	1.0				
HA2	10	3.0				
	14.3, 25, 38	1.0				
HA3	14.3	3.0				
	25, 38, 50	1.0				
HA4	14.3	3.0				
	25, 38, 50, 75	1.0				
VA5	25, 37.5, 50, 75, 100	1.0				
VA6	14.3	3.0				
PSA6, 7	25, 37.5, 50, 75, 100	1.0				
HK1	10	3.0				
PSK1	19	1.0				
DAP560, 1000	14.3	3.0				
1000X	25 ~ 100	1.0				
DAP1500,	14.3, 25	3.0				
1500X	38 ~ 100	1.0				

Table 1. Actuator stroke and accura	C
-------------------------------------	---

# LIST OF FEATURES

Function
Any split-range value can be specified.
The control valve can be fully closed or opened securely when the desired percentage of input signal is reached.
The relationship between input signal and valve travel that is appropriate for the process can be defined by using a 16-point line graph.
Valve motion can be reliably monitored by transmitting the valve travel.

## FUNCTIONAL SPECIFICATIONS

	ltem	Specification				
Applicable actu	ator	Pneumatic single and double acting, linear and rotary motion actuator				
Input signal		4-20 mA DC (Configurable to any required range for split range.)				
		Minimum driving current: 3.85mA *1				
Communicatio	n system	SFN communication (Model AVP300/301/302)				
		HART6 communication (Model AVP302)				
Output signal		4-20 mA DC (Travel transmission) *2				
Input resistance		300 Ω typically / 20 mA DC (Model AVP300/AVP301 Waterproof, Flameproof)				
		350 Ω typically / 20 mA DC (Model AVP300/AVP301 FM/CCC/ATEX/CNS Intrinsically safe)				
		400 Ω typically / 20 mA DC (Model AVP302)				
Lightning prote	ection	Peak value of voltage surge: 12 kV				
		Peak value of current surge: 1000 A				
Flow characteri	stics	Linear, Equal percentage, Quick opening				
		Custom user characteristics (16 points)				
Manual operati	on	Auto/Manual external switch (Not available for double acting actuator)				
Supply air press	sure	140 to 700 kPa				
Air	For single acting	4 L/min (N) or less: with steady supply air pressure of 140 kPa {1.4 kgf/cm <sup>2</sup> } and output of 50 %				
consumption	actuator	5 L/min (N) or less: with steady supply air pressure of 280 kPa {2.8 kgf/cm²} and output of 50 %				
		6 L/min (N) or less: with steady supply air pressure of 500 kPa {5.0 kgf/cm <sup>2</sup> } and output of 50 %				
	For double acting actuator	10 L/min (N) or less: with steady supply air pressure of 400 kPa {4.0 kgf/cm <sup>2</sup> }				
Output balance	d pressure	55±5 % for double acting actuator only (without a load, and when output air pressure is balanced)				
Maximum air deliver flowrate	For single acting actuator	110 L/min (N) maximum at 140 kPa {1.4 kgf/cm <sup>2</sup> }				
	For double acting actuator	250 L/min (N) maximum at 400 kPa {4.0 kgf/cm <sup>2</sup> }				
Air connection	S	Rc1/4 or 1/4NPT internal thread				
Electrical conne	ections	G1/2, 1/2NPT or M20×1.5 internal thread				
Ambient tempe	erature limits	General, FM Explosionproof, FM Intrinsically safe models : -40 to +80°C				
		TIIS / KCs (main unit model number "S") Flameproof models : -20 to +55°C				
		ATEX / KCs (main unit model number "H") / IECEx / CCC / INMETRO / CNS Flameproof models : -40 to +75°C				
		ATEX / CCC / CNS Intrinsically safe models : -40 to +60°C				
Ambient humio	lity limits	10 to 90 %RH				
Vibration chara	cteristics	20 m/s <sup>2</sup> , 5 to 400 Hz (with standard mounting kit on Azbil Corporation's HA actuator)				
Finish		Baked acrylic				
Color		Dark blue				
Material		Cast aluminum				
Weight		2.5 kg (3.2 kg with a pressure regulator with filter model KZ03).				
		(If combined with a reversing relay for a double-acting actuator, add 0.3 kg to the weight.)				
Performance	Accuracy	±1.0% F.S.(±2.5 % with user-defined flow characteristics)				
		$\pm 3.0$ % FS if the feedback lever angle is outside the $\pm 4^{\circ}$ to $\pm 20^{\circ}$ range (refer to Table 1 of 2nd page)				
		There is an additional 0.5 % FS (input error) if 4 mA $\leq$ input signal span $< 8$ mA				
	Travel transmission accuracy*2	±1 %F.S. (±2.5 % with user-defined flow characteristics)				
	Stroke coverage	14.3 to 100 mm Stroke (Feedback Lever Angle ±4° to ±20°)				
Enclosure class	ification	JIS C0920 watertight, NEMA type 4X, IP66				

# No. SS2-AVP300-0100

# **Azbil Corporation**

Item	Specification				
Structure	TIIS Flameproof	Ex d IIC T6 X			
	KCs Flameproof	Ex d IIC T6			
		Flameproof cable gland must be KCs Ex d IIC approved.			
	FM Explosionproof	Explosionproof: Class I, Division 1, Group A, B, C, D			
		Dust-ignition: Class II, Division 1, Group E, F, G			
		Suitable: Class III, Division 1			
		Flameproof: Class I, Zone 1, AEx d IIC T6 at T <sub>amb</sub> <80°C			
		NEMA Type 4X			
		The wiring conduit cable gland and electrical wiring must be compliant with the National Electrical Code (NEC).			
	FM Intrinsically safe	Intrinsically safe: Class I, II, III, Division 1, Group A, B, C, D, E, F, G, T4 Intrinsically safe: Class I, Zone 0, AEx ia IIC T4			
		Nonincendive: Class I, Division 2, Group A, B, C, D, T5 Suitable: Class II, III, Division 2, Groups F, G, T4 NEMA Type 4X, IP66			
		The barriers should be FM recognized types and comply with the following conditions as follows:			
		Input circuit(terminals ±IIN) Model AVP300/AVP301: 12.02≤V <sub>max</sub> ≤30 V, I <sub>max</sub> =100mA, Pi=1 W,			
		Ci=18.26 nF, Li=0.22 mH Model AVP302: 12.02≤V <sub>max</sub> ≤30 V, I <sub>max</sub> =100 mA, Pi=1 W, Ci=41 nF, Li=0.22 mH			
		Output circuit(terminals ±OUT) Model AVP301: V <sub>max</sub> =30 V, I <sub>max</sub> =100 mA, Pi=1 W, Ci=22 nF, Li=0.22 mH			
		Installation should comply with NEC.			
	ATEX Flameproof	II 2 G Ex db IIC T6 Gb −40 °C≤T <sub>amb</sub> ≤+75 °C			
		IEC IP66			
		Flameproof cable gland must be ATEX Ex db IIC approved.			
		Note: IP66 waterproof and dust-proof performance can be assured by installing an appropriate cable gland.			
	ATEX Intrinsically	II 1 G Ex ia IIC T4 Ga			
	safe	II 1 D Ex ia IIIC T135°C Da			
		IEC IP66			
		The barriers should be ATEX certified types and comply with the following condition as follows:			
		Input circuit (terminals ±IIN) Model AVP300/AVP301: Ui=30 V, Ii=100 mA(resistively limited), Pi=1 W, Ci=5 nF, Li=0.22 mH Model AVP302: Ui=30 V, Ii=100 mA(resistively limited), Pi=1 W, Ci=41 nF, Li=0.22 mH			
		Output circuit (terminals ±IOUT) Model AVP301: Ui=30 V, Ii=100 mA(resistively limited), Pi=1 W, Ci=22 nF, Li=0.22 mH			
	CCC Flameproof	Ex d IIC T6 Gb Flameproof cable gland must be CCC Ex d IIC approved.			
	CCC Intrinsically safe	Ex ia IIC T4 Ga, Ex iaD 20 T135			
		The barriers should be CCC certified types and comply with the following condition as follows:			
		Input circuit (terminals ±IIN) Model AVP300/AVP301: Ui=30 V, Ii=100 mA, Pi=1 W, Ci=5 nF, Li=0.22 mH Model AVP302: Ui=30 V, Ii=100 mA, Pi=1 W, Ci=41 nF, Li=0.22 mH			
		Output circuit (terminals ±IOUT) Model AVP301: Ui=30 V, Ii=100 mA, Pi=1 W, Ci=22 nF, Li=0.22 mH			
	Combination of CCC Flameproof and	When used as CCC Flameproof, it complies CCC Flameproof approval as above.			
	Intrinsically safe	When used as CCC Intrinsically safe, it complies CCC Intrinsically safe approval as above.			
	IECEx Flameproof	Ex db IIC T6 Gb			
		IEC IP66			
		Flameproof cable gland must be IECEx Ex db IIC approved.			
		Note: IP66 waterproof and dust-proof performance can be assured by installing an appropriate cable gland.			

ltem		Specification
Structure	INMETRO	Ex db IIC T6 Gb
	Flameproof	Flameproof cable gland must be INMETRO Ex db IIC approved.
		<i>Note: IP66 waterproof and dust-proof performance can be assured by installing an appropriate cable gland.</i>
	CNS Flameproof	Ex db IIC T6 Gb
	IEC IP66	
		Flameproof cable gland must be CNS Ex db IIC approved.
		<i>Note: IP66 waterproof and dust-proof performance can be assured by installing an appropriate cable gland.</i>
	CNS Intrinsically safe	Ex ia llC T4 Ga
		IEC IP66
		The barriers should be CNS certified types and comply with the following
		condition as follows:
		Input circuit (terminals ±IIN)
		Model AVP300/AVP301: Ui=30 V, Ii=100 mA, Pi=1 W, Ci=5 nF, Li=0.22 mH
		Model AVP302: Ui=30 V, Ii=100 mA, Pi=1 W, Ci=41 nF, Li=0.22 mH
	Output circuit (terminals ±IOUT)	
		Model AVP301: Ui=30 V, Ii=100 mA, Pi=1 W, Ci=22 nF, Li=0.22 mH
CE Marking	EN61326-1:2013 (EMC	c), EN50581:2012 (RoHS)
Configuration tools	Field Communication	Software(Model CFS100)

\*1 In case of model AVP301 when signal input is less than 3.85 mA, output current will be burnout(up or down (indefinite)).

\*2 This applies only to positioners with travel transmission (model AVP301). In this case, a power supply circuit for travel transmission is required.

Note: Depending on the inner diameter and length of the air pipe, automatic setup might not be sufficient to realize the optimum operation. In such a case, please specify the relevant parameters.

## Conditions of supply air (JIS C1805-1 (2001))

Item	Specification
Particles	Maximum diameter 3 µmm
Oil mist	Less than 1 ppm at mass
Humidity of the air supply	The dew point should be at least 10°C lower than the temperature of this device.

To meet the above specifications for instrument air, install the air purification devices listed below properly in the specified installation location.

#### Examples of air purification devices

Installation	Air purification device	SMC corporation	CKD corporation		
Compressor outlet or main line	Line filter	AFF series	AF series		
	Mist separator	AM series			
Terminal device	Mist separator	AM150 or AM250 series	M3000S type		

# **MODEL SELECTION**

#### **Basic model number**

AVP300	Analog signal (4 to 20 mA DC) without position transm		-	(1)	(2)	(3)	(4)	(!
AVP301	Analog signal (4 to 20 mA DC) with position transmission	on						
AVP302	Analog signal (4 to 20 mA DC) HART protocol							
		(Air pipes, conduit connectio	ns)					
	Water-proof	(Rc 1/4, G1/2)	.,	Х				
	Water-proof	(1/4 NPT, 1/2 NPT)		P				
	Water-proof	(1/4 NPT, M20×1.5)		Q				
	TIIS Flameproof with cable gland <sup>*1</sup>	(Rc 1/4, G1/2)		E				
	KCs Flameproof	(Rc 1/4, G1/2)		S				
	KCs Flameproof	(1/4 NPT, 1/2 NPT)		H				
	FM Explosionproof and Flameproof	(1/4 NPT, 1/2 NPT)		F				
	FM Intrinsically safe	(1/4 NPT, 1/2 NPT)		M				
	FM Intrinsically safe	(1/4 NPT,G1/2)		6				
	ATEX Flameproof	(1/4 NPT, M20×1.5)		C				
	ATEX Flameproof	(1/4 NPT,1/2NPT)		Y				
	ATEX Intrinsically safe	(1/4 NPT, M20×1.5)		L				
(1) Main unit model	ATEX Intrinsically safe	(1/4 NPT,1/2 NPT)		U				
number	ATEX Intrinsically safe	(Rc 1/4,G1/2)		V				
munioer	CCC Flameproof	(1/4 NPT, 1/2 NPT)		B				
	CCC Flameproof	(1/4 NPT, M20×1.5)		N				
	CCC Intrinsically safe and Flameproof	(1/4 NPT, 1/2 NPT)		R				
	CCC Intrinsically safe and Flameproof	(1/4 NPT, M20×1.5)		W				
	IECEx Flameproof	(1/4 NPT, 1/2 NPT)		т Т				
	IECEx Flameproof	(1/4 NPT, M20×1.5)		G				
	INMETRO Flameproof	(1/4 NPT, 1/2 NPT)		3				
	INMETRO Flameproof	(1/4 NPT, M20×1.5)		2				
	CNS Flameproof	(1/4 NPT, 1/2 NPT)		D				
	CNS Flameproof	(1/4 NPT, M20×1.5)		1				
	CNS Intrinsically safe	(1/4 NPT, M20×1.5)		Z				
	CNS Intrinsically safe	(1/4NPT, 1/2 NPT)		0				
	Standard (Baked Acylic)	(1/11111,1/21111)		0	S			
(2) Finish	Corrosion proof (Baked polyurethane)				B			
(2) 1 111311	Silver finish (Baked Acrylic)				D			
	Direct Action (standard) - Air pressure increases with Co	ontrol signal increase			D	D		
(3) Positioner action * 2	Reverse Action (reverse positioning) Airpressure decrease					R		
	Reverse Action (reverse positioning) An pressure decrea	(Pressure gauge sc	ale, N	lax reg	gulator s			
	$140 \le Ps \le 150 \text{ kPa}$	(200 kPa, 400 kPa)					1	1
	$150 < Ps \le 300 \text{ kPa}$	(400 kPa, 400 kPa)					2	1
(4) Supply air pressure	$300 < Ps \le 400 \text{ kPa}$	(600 kPa, 400 kPa)					3	1
type	$400 < Ps \le 450 \text{ kPa}$	(600 kPa, 700 kPa)					4	1
	$450 < Ps \le 700 \text{ kPa}$	(1000 kPa, 700 kPa)					5	1
	450 < F3 ≤ 700 KF4						5	t
	(kgf/cm <sup>2</sup> ) * 3							(
(5) Pressure units	MPa							
(3) FICSSUIC UIIIIS	bar							
	Dai							1

\*1. Model AVP300/AVP302 includes one flameproof cable gland, and model AVP301 includes two.

\*2. When the input signal (power) is shut off, select direct action to make the output air pressure of this device zero, and reverse action to make the output at the maximum air pressure (supply air pressure). Positioner action differs from actuator and control valve action, so be careful in selecting the positioner's action. If double acting actuator are using, not available code "R".

\*3. Items in parentheses are for overseas use. As such, they cannot be used in Japan.

6

#### **Individual specifications**

Following shows default and optional settings of each configurable parameter of AVP. Unless otherwise specified, the Smart Valve Positioner will be shipped in the following configuration.

Input control signal	4 to 20 mA	The minimal span for custom range = 4 mA
Output characteristic *1	Liner	EQ or QO can be ordered or set by user.
Valve action *2	Direct (Push down to close)	Reverse (Push down to open) can be ordered or set by use
Output signal for position transmission	4 to 20 mA	DE also selectable

\*1. Refer to the following when selecting the input/output characteristics.

\*2. Positioner action differs from actuator and control valve action, so be careful in selecting the positioner's action.



Selection of input characterization

The flow characteristic of a control valve is set by selecting the valve plug characteristic, and the inputoutput characteristics of the positioner must be specified as linear. However, if the valve plug flow characteristic, which depends on the control valve's shape and structure, does not meet requirements, you can correct the overall flow characteristic of the control valve by specifying "equal percentage" or "quick opening" for the input-output characteristics of the positioner, as shown in Table 2.

#### Table 2. Control valve flow characteristics correction by the positioner

Characteristic of valve plug	Input-output characterization of positioner	Overall flow characteristic of control valve
Linear	Linear Quick opening	
Linear	EQ%	EQ%
EQ%	Quick opening	Linear

Note: If the valve plug characteristic is "quick opening," the overall flow characteristic of the control valve cannot be linear even if "equal percentage" is set for the positioner's input-output characteristics. (This is because when the valve plug characteristic is "quick opening," the control valve works as an ON/OFF valve and it is difficult to correct its characteristics by changing the setting of the positioner.)

#### No. SS2-AVP300-0100

#### **Azbil Corporation**

		Accessory Selection -	(6)	(7)	(8)	(9)	-	(10)
		Without regulator	X					
(6) Regulator with filter	r	With model KZ03 regulator (attached to main unit) *1	л 1					
(b) Regulator with litter	L	With model KZ03 regulator (with mounting plate for separate installation)	2					
(7) Mounting bracket m	aata	No mounting plate	2	Х				
rial (mounting plate/bo		SUS304 / SUS304		D				
fiai (mounting plate/00	(113)			D	X	v		
		No mounting plate						
		PSA1, PSA2, PSK1			Y			
		New model PSA3, 4 (produced after 2000), VA1 to 3 (produced after May. '83)	-		Y			
		PSA3, PSA4 for existing valves produced on/before 1999			Y			
		PSA6, VA4 to 6 (produced after May. '83)			Y			
		PSA7			Y	-		
		HA1			Y			
		HA2, HA3, HL2, HL3			Y			
	tors	HA4, HL4			Y	N		
	ctua	HK1, VM1 *2	_		Y	K		
	log ac	VM12 for model VSP *3			Y	В		
	ctin	VR1			Y	V		
	Single-acting actuators	VR2, VR3			Y	R		
	Sing	VR3H			Y	6		
		RSA1			Y	F		
		RSA2			Y	U		
		GOM 83S, GOM 84S, GOM 103S			Y	G		
		GOM 124S			Y	М		
(8)(9) Mounting		VA1 to 3 (produced before Apr. '83, former model Motion Connector), 800-1, 2, 3	3 *4		Y	W		
bracket for attachment to actuator *9		(VA4,5(produced before Apr. '83, former model Motion Connector), 800-4, 5) *4			Y	J		
to actuator 3		Actuators of other manufacturers			Se Tab	e		
		VP5, 6 *5	-		<u>Iab</u>			
		VP7 *5			Y			
		SLOP560, 1000, 1000X *5 (stroke:100mm max)			Y			
		SLOP1500, 1500X *5 (stroke:100mm max)			Y			
	rs	DAP560, 1000, 1000X *5 (stroke:100mm max)			Y			
	lato	DAP1500, 1500X *5 (stroke:100mm max)			Y			
	actu	DAP560 (VFR : 8 to 12B)			L			
	Double-acting actuators	DAP560 (VFR : 14B, 16B)			L			
	-act	DAP560 (VDC, VDN, VST : 16B)						
	ıble	DAP1000,1000X (VDC, VDN, VST : 16B)						
	Dot	DAP1500,1500X (VDC, VDN, VST : 16B)	-		L			
		GOM64LM,84LM (springless, vertical, double acting) *6			G			
		GOM64LM,84LM (springless, vertical, double acting) *7			G			
		GOM124LM (springless, vertical, double acting)*6			G			
		GOM124LM (springless, vertical, double acting)*7			G			
		Actuators of other manufacturers			Se Tab			
		None						X
		Explosion-proof universal elbow (SUS304 G1/2) (1)						A
(10) Option		Explosion-proof universal elbow (SUS304 G1/2) (2)						C
		Mounting screw Unify (5/16-18UNC) (Electrical conduit connection only suppor	ts 1/2	NPT)				Т
		Double-acting reversing relay *8						W

\*1. Select the code "1" only when the direction of drain of the pressure regulator with filter on the control valve is downward(ground).

\*2. In case "VM" type actuator is required following conditions, 1. select model "VCT" for the body, 2. the existing positioner should be HEP or VPE, 3. yoke should be model HK. If another spec. is required, contact your sales representative.

\*3. Additional support bracket is required.

\*4. Consult with sales representative in case of no mounting hole on the side of valve yoke.

\*5. In case of double acting actuator, a reversing relay unit required.

\*6 In case of valve body is not butterfly valve of Azbil Corporation.

\*7 In case of valve body is butterfly valve of Azbil Corporation.

\*8 If reverse action is selected for positioner action, this option cannot be selected.

\*9 Accuracy differs depending on the actuator stroke (see table 1).

#### Table 3. Mounting bracket for single acting actuator

(8)(9) Mounting bracket for pneumatic actuator	Code
Motoyama Mfg. 2800 series 240, 280, 330, Nihon Koso A100 series 270, 320 $^{\ast}$	TA
Motoyama Mfg. 2800 series 400, 500S, 500L,Nihon Koso A100 series 400, 500 *	ТВ
Motoyama Mfg. 2800 series 650S, 650L*	TC
Motoyama Mfg. 2800 series 240, 280, 330 (with side manual handle)	TD
Motoyama Mfg. 2800 series 400, 500S, 500L (with side manual handle)	TE
Motoyama Mfg. 2800 series 650S, 650L (with side manual handle)	TF
Motoyama Mfg. 3800 series (multi-spring type) N24, N28, N33S	TJ
Motoyama Mfg. 2922 series (Gyrol-I) G.R.I 280H, 330H, 400HS, 400H, 500H	TL
Motoyama Mfg. 3993 series (Gyrol-II) 2911-1M series 280, 330, 400	TG
Nihon Koso 5100L series 240, 280 *	TP
Nihon KOSO 5100L Series 330,400,5200LA Series 400 *	TQ
Nihon Koso 5200L series 218, 270, 350 *	TR
NIHON KOSO 5200LA SERIES 450 *	TV
Masoneilan 37, 38 series #9, #11 *	MA
Masoneilan 37, 38 series #13 *	MB
Masoneilan 37, 38 Series #13 (w/Side handle)	ME
Masoneilan 37, 38 series #15, #18 *	MC
Masoneilan 37, 38 series #15, #18 (with side manual handle)	MF
Masoneilan type 35002 series Camflex II #41/2, #6, (Valve size 1 inch - 4 inches)	MG
Masoneilan type 35002 Camflex II #7 (Valve size 6 inches - 12 inches)	MH
Masoneilan 37,38 Series #11 *	MJ
Masoneilan 82,83 Series #13 (w/Side handle w/o Side handle)	MK
Masoneilan 82,83 Series #15 *	ML
Masoneilan 82,83 Series #18 *	ММ

(8)(9) Mounting bracket for pneumatic actuator	Code
Fisher 657, 667 series size 40	FB
Fisher 657, 667 series size 45, 50	FC
Fisher 657, 667 series size 60	FD
Emerson Valves & Controls Japan (Formerly Kitamura Valve) AK09S,12S,15S	KA
Emerson Valves & Controls Japan (Formerly Kitamura Valve) AG06	KG
Emerson Valves & Controls Japan (Formerly Kitamura Valve) AG09S	KH
Emerson Valves & Controls Japan (Formerly Kitamura Valve) AG13S	KJ
Emerson Valves & Controls Japan (Formerly Kitamura Valve) AW13S	KV
Emerson Valves & Controls Japan (Formerly Kitamura Valve) AW17S	KW
Emerson Valves & Controls Japan (Formerly Kitamura Valve) AW20S	KT
Emerson Valves & Controls Japan (Formerly Kitamura Valve) AW28S	KD
KITZ B Series BS-2,BSW-2	B2
KITZ B Series BS-3,BSW-3	B3
KITZ B Series BS-4,BSW-4	B4
KITZ B Series BS-5,BSW-5	B5
KITZ B Series BS-6,BSW-6	B6
Emerson(EL-O-MATIC) E25,40,65,100,200,350	RA
Emerson(EL-O-MATIC) E600,950,1600,P2500,P4000	RB
Hisaka Mfg. TS-1	H1
Hisaka Mfg. TS-2	H2
Hisaka Mfg. TS-3	H3
Hisaka Mfg. TS-4,Old type TS-5(Mounting screw M8)	H4
Hisaka Mfg. New TS-5(Mounting screw M10),TS-6	H6
TOMOE Valve Z Series Z-06S,08S,11S,13S	EA
TOMOE Valve T-matic 3Q-1,2,3,4	E3
Nakakita Seisakusho Co. dia. 420, 430, 460, 480	JB

\* Select in the case of without manual handle or with manual handle mounted on top of the actuators.

#### Table 4. Mounting bracket for double acting actuator

(8)(9) Mounting bracket for pneumatic actuator		Code
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AK09, AK12, AK15	*	KA
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AG06	*	KG
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AG09	*	KH
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AG13	*	KJ
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AW13	*	KV
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AW17	*	KW
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AW17-HG (w/manual gear handle)	*	KB
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AW20	*	KT
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AW20-HG (w/manual gear handle)	*	KC
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AW28	*	KD
Emerson Valves & Controls Japan (Formerly Kita- mura Valve) AW28-HG (w/manual gear handle)	*	KE
KITZ B series B-2	*	B2
KITZ B series B-3	*	B3
KITZ B series B-4	*	B4

(8)(9) Mounting bracket for pneumatic actuator		Code
KITZ B series B-5	*	B5
KITZ B series B-6	*	B6
Emerson (EL-O-MATIC) E25, 40, 65, 100, 200, 350	*	RA
Emerson(EL-O-MATIC) E600,950,1600,P2500,P4000	*	RB
TOMOE Valve Z Series Z-06,08,11,13	*	EA
TOMOE Valve T-matic 3I-1,2,3,4	*	E3
T.V. Valve AT4-80	*	V1
T.V. Valve AT4-100	*	V2
T.V. Valve AT4-120	*	V3
T.V. Valve AT4-150	*	V4
T.V. Valve AT4-180	*	V5
Nihon KOSO AT550,AT600,AT650,AT700	*	TW

\* In case of double acting actuator, a reversing relay unit required.

# DIMENSIONS For single acting actuator without pressure regulator with filter

[Unit: mm]



VR1

VR2, 3

GOM83S, 84S, 103S

GOM124S

YV

YR

YG

YM

32

ф

64

90min

# For single acting actuator with pressure regulator with filter

No. SS2-AVP300-0100

[Unit: mm]



Electrical connection*1	Air piping connection*2
G1/2	Rc1/4
1/2NPT	1/4NPT
M20×1.5	1/4NPT



Extension lever	Actuator model	Code	
	PSA1, 2, PSK1	YS	
No	HA1	YA	
	HA2, 3	YT	
	HK1	YK	
	PSA3, 4	YQ	
	VA1 to 3		
	PSA6	YL	
Yes	PSA7	Y8	
	HA4	YN	
	VA4 to 6	YL	
	VR1	YV	
	VR2, 3	YR	
	GOM83S, 84S, 103S	YG	
	GOM124S	YM	

## For double acting actuator with reversing-relay

#### [Unit: mm]

#### Without pressure regulator with filter





#### With pressure regulator with filter



12

HART\* is a registered trademark of FieldComm Group.

Please read "Terms and Conditions" from the following URL before ordering and use. https://www.azbil.com/products/factory/order.html

Specifications are subject to change without notice.

# Azbil Corporation Advanced Automation Company

1-12-2 Kawana, Fujisawa Kanagawa 251-8522 Japan URL: https://www.azbil.com/

(16)

